

	LUMINAIRE SCHEDULE							
TYPE	DESCRIPTION	MANUFACTURER	MANUFACTURER CATALOG MUNBER	LAMPS	NO. OF BALLASTS	INPUT WATTS	VOLT	REMARKS
SA	18" LED LOW BAY	STARTEK	AVND-18-H-35K-80-CTBD-STEMWXX-U	LED	LED DRIVER	64	UNV	STEM MOUNT ON EXISTING STRUCTURE.
SAE	18" LED LOW BAY	STARTEK	AVND-18-H-35K-80-CTBD-STEMWXX-U-EMB10	LED	LED DRIVER	64	UNV	STEM MOUNT ON EXISTING STRUCTURE.
RA	EXISTING FLUORESCENT TROFFER	NA	NA	FL	2	80	277	RELOCATE PER DRAWINGS. PROTECT FIXTURE PER DETAIL G003.
RB	6" DIA LED DOWNLIGHT	LITHONIA	LDN6 35/10 L06-CTBD-CTBD-MVOLT-GZ10	LED	LED DRIVER	10	UNV	
RC	2X2 LED TROFFER	LITHONIA	2BLTBA2-33L-ADSM-GZ10-LP835	LED	LED DRIVER	26	UNV	PROTECT FIXTURE PER DETAIL G003.
RCE	2X2 LED TROFFER	LITHONIA	2BLTBA2-33L-ADSM-GZ10-LP835-EL14L	LED	LED DRIVER	26	UNV	PROVIDE WITH EMERGENCY BATTERY PACK. PROTECT FIXTURE PER DETAILS G003.
RD	2X4 LED TROFFER	LITHONIA	2GTL-4-48L-LP835	LED	LED DRIVER	36	UNV	PROTECT FIXTURE PER DETAIL G003.
RDE	2X4 LED TROFFER	LITHONIA	2GTL-4-48L-LP835-EL14L	LED	LED DRIVER	36	UNV	PROVIDE WITH 90 MIN.EMERGENCY BATTERY PACK. PROTECT FIXTURE PER DETAILS G003.
PA	ARCH. PENDANT	INNERMOST	CHELSEA SERIES	LED	LED DRIVER		UNV	PROTECT BOX AT CEILING PER G003.
РВ	LINEAR PENDANT MOUNTED FIXTURE	LEDALITE	TM-0-6-L-935-L-20-Q-20-04-D-E-1-NN-CTBD-TBD	LED	LED DRIVER	35	UNV	PROTECT BOX AT CEILING PER G003.
PBE	LINEAR PENDANT MOUNTED FIXTURE	LEADALITE	TM-0-6-L-935-L-20-Q-20-04-D-E-1-E-NN-CTBD-TBD	LED	LED DRIVER	35	UNV	PROVIDE WITH 90 MIN. EMERGENCY BATTERY PACK. PROTECT BOX AT CEILING PER G003.
XA	EXTERIOR MOUNTED EGRESS LIGHT	LUMINAIRE LED	AEL-24-NODIM-20W-TBD-277-DP-CTBD-PC	LED	LED DRIVER	20	UNV	PROVIDE WITH INTEGRAL PHOTOCELL.
XAE	EXTERIOR MOUNTED EGRESS LIGHT	LUMINAIRE LED	AEL-24-NODIM-20W-TBD-277-DP-CTBD-PC	LED	LED DRIVER	20	UNV	PROVIDE WITH INTEGRAL PHOTOCELL. SEE NOTE 1 BELC
E1	LED EXIT SIGN	LITHONIA	EDGR-CTBD-XX-RMR-EL	LED	LED DRIVER	4.3	UNV	PROVIDE WITH 90 MIN. EMERGENCY BATTERY BACK U
E2	LED EXIT SIGN	LITHONIA	LQC-CTBD-XX-R-ELN	LED	LED DRIVER	4.3	UNV	PROVIDE WITH 90 MIN. EMERGENCY BATTERY BACK U
E3	AREA OF RESCUE ASSISTANCE SIGN	CORNELL	SN-B SERIES	LED	LED DRIVER	4.3	UNV	PROVIDE WITH 90 MIN. EMERGENCY BATTERY BACK U

CTBD-COLOR TO BE SELECTED FROM MANUFACTURER'S STANDARD COLOR PALLETTE AT SHOP DRAWING STAGE.

TBD-OPTION TO BE DECIDED AT SHOP DRAWING STAGE.

LUMINAIRE SCHEDULE 2

5 W Hargett Street 310 Raleigh, NC 27601 (919) 838-9337 aoarchitect.com




Sigma Engineered Solutions, PC
5909 Falls of Neuse Rd.
Suite 101
Raleigh NC 27609
Ph: 919.840.9300
www.sigmaes.com
Sigma Project #: 22049
NC ENG LIC# C-2490

PROJECT No.: 2219


HURCF

CLC PHASE 1B RENOVAT MHITE PLAINS UNITED METHODI

SEALS:







ELECTRICAL RISER & SCHEDULES

E400